



- Auto-Ranging
- 2-Meter drop resistance
- Data hold function
- Relative measurement mode (REL)
- Bright backlit display
- Low battery indicator
- Continuity beeper

The DMM-135B is a pocket-sized digital multimeter that can measure AC/DC voltage and current, resistance, capacitance, diodes, and continuity. It's a cost-effective, portable multimeter suitable for on-the-go use.

DIGITS	1,999 Counts
DC VOLTAGE	200m / 2 / 20 / 200 / 250 V $\pm(0.8\%+1)$
AC VOLTAGE	200m / 2 / 20 / 200 / 250 V $\pm(1.0\%+2)$
DC CURRENT	200 μ / 2000 μ / 20m / 200m / 2 / 10 A $\pm(1.0\%+3)$
AC CURRENT	200 μ / 2000 μ / 20m / 200m / 2 / 10 A $\pm(1.2\%+3)$
RESISTANCE	200 / 2k / 20k / 200k / 2M / 20M / 200 M Ω $\pm(0.8\%+2)$
CAPACITANCE	2n / 20n / 200n / 2 μ / 20 μ / 200 μ F $\pm(3.0\%+5)$
POWER	1.5 V Battery (AAA $\times$ 2)
DIMENSIONS	137 $\times$ 77 $\times$ 47 mm
Weight	206 g
Accessories	test leads , manual

TECPEL®

泰菱有限公司