

1358 Sound Analyzer Real Time



Real-time 1/1-Octave and 1/3-Octave analysis.

Wide linearity range of 100dB.

Large display with backlighting.

Real time clock with calendar.

Memory max. 10000 records of Lp data.

RS-232 interface.

Applicable standards	IEC 60651 Type2, IEC 60804 Type2, BS EN 6065, 1994, IEC 1260-1995		
Microphone	1/2-inch Electret condenser microphone		
Accuracy	+/- 1.5dB (ref 94dB @ 1KHz)		
Measurement range	30dB to 130dB		
Measurement function	Lp , Leq , LE , Lmax , Lmin		
Frequency range	25Hz ~ 10KHz		
Frequency weighting	A ,C, Flat		
Time weighting	Fast , Slow		
Display	160x160 dot matrix display with back light · Sound level meter display Numerical : 4 digits, up data cycle 0.5s, resolution 0.1dB Bar graph : Scale range 100dB , update cycle 0.125s Real time clock : Year, Month, Day, Hour, Minute, Second		
Analyzer level range	5 ranges in 10dB step ; 20-90dB/30-100dB/40-110dB/50-120dB/60-130dB		
1/1 Octave and 1/3 Octave band filters	1/1 Octave band center frequencies : (9 bands) 31.5Hz, 63Hz, 125Hz, 250Hz, 500Hz, 1KHz, 2KHz, 4KHz, and 8KHz. 1/3 Octave band center frequencies : (27 bands) 25Hz, 31.5Hz, 40Hz, 50Hz, 63Hz, 80Hz, 100Hz, 125Hz, 160Hz, 200Hz, 250Hz, 315Hz, 400Hz, 500Hz, 630Hz, 800Hz, 1KHz, 1.25KHz, 1.6KHz, 2KHz, 2.5KHz, 3.15KHz, 4KHz, 5KHz, 6.3KHz, 8KHz 10KHz.		
Memory capacity	Mode/Store mode	Manual	Auto
	Sound level meter	1024 data sets	10000 data sets
	1/1-octave analysis	1024 data sets	6140 data sets
	1/1-octave analysis	1024 data sets	3070 data sets
Signal output	AC output : 2 Vrms (at full scale) DC output : 10mVDC / dB Serial interface : RS-232 , 9 pin D-sub		
Power	4 pcs of C size 1.5V (LR14) batteries		
DC power supply	6V, 1A		
Battery life	Approx. 2hrs		
Operating Temp./Hum.	0°C to 40°C , 10 to 80% RH		
Dimensions & Weight	34.5(H)×10(W)×6(D) cm & Approx. 950g (including batteries)		
Accessories	Instruction manual, Battery x 4, Carry case, Software, RS-232 cable, 9 Pin to 25 Pin gender changer, Adjustment screwdriver, Wind shield, 3.5f plug, AC/DC Adaptor.		