

LCR-613 100KHz Digital LCR Meter



FUNCTIONS	RANGES	ACCURACY
INDUCTANCE (H)	20uH/200uH/20mH/200mH/ 2000mH/20H/200H/2000H/20KH	±(0.5%+5)
CAPACITANCE(F)	200pF/200pF/2nF/20nF/200nF/ 2000nF/20uF/200uF/2000uF/20mF	±(0.5%+5)
RESISTANCE(Ω)	20Ω/200Ω/2KΩ/20KΩ/200KΩ/ 2MΩ/20MΩ/200MΩ	±(0.3%+5)
TEST FREQUENCY	100Hz/120Hz/1KHz/10KHz/100KHz	√
TEST VOLTAGE	0.6Vrms	√
TEST PARAMETER	L/C/R/DCR/Q/D/θ/ESR	√
MAX. DISPLAY		19999
D/Q MAX. DISPLAY		1999
D/Q RESOLUTIONS	0.001	√
AUTO RANGE		√
REAL TIME DISPLAY OF TEST FREQUENCY		√
TEST MODE	SERIES/PARALLEL	√
AUTO POWER-OFF		√
LOW Battery DISPLAY	≤6.8V	√
DATA HOLD		√
RELATIVE TEST		√
USB TRANSMISSION		√
PC DATA RECORD		60000
LCD BACKLIGHT		√
BAR GRAPH		26 段
DEVIATION RATIO MEASUREMENT		√
FILTER FUNCTION		√
CALIBRATION FUNCTION		√
OUTPUT IMPEDANCE	120Ω	√
LCR AUTO IDENTIFICATION MEASUREMENT		√
POWER	9V BATTERY(6F22) OR USB POWER	
LCD DIMENSION	40 X 63mm	
WEIGHT/DIMENSION	374g / 96 X 193 X 47mm	
ACCESSORY	Standard Accessories Battery, SMD Test Clip, USB Data Cable, Software CD, Adapter Socket, Shorting Plate	